



30kW - 400 kW Generator Sets

Generator sets come self-contained, with trailer or skid-mounted fuel-tank bases for easy travel and delivery. Units range from 30kW portable units to 2 MW power modules with utility-grade switchgear. Sound-attenuated XQ modules are quiet and all equipment is EPA certified.

From building construction and disaster relief, to concert-stage lighting and peak-time utility power - Michigan CAT has the equipment to fit your needs.

SPECIFICATIONS

Model	Generator Set Fuel Consumption	Tank Capacity (gal)	Electrical	Weight (With Trailer)	Dimensions (With Trailer)
30 kW	100% load = 2.4 75% load = 1.8 50% load = 1.3	58.6	104 amps at 208 v. 45 amps at 480 v.	6,480 lbs	6.3'W x 7.3'H x 15.4'L
80 kW	100% load = 6.0 75% load = 4.80 50% load = 3.6	167	278 amps at 208 v. 120 amps at 480 v.	8,120 lbs	6'9"W x 7'8"H x 16'L
100 kW	100% load = 7 75% load = 5.25 50% load = 3.5	182	347 amps at 208 v. 150 amps at 480 v.	8,470 lbs.	6'9"W x 7'8"H x 16'L
150 kW	100% load = 11.2 75% load = 8.5 50% load = 5.9	210	520 amps at 208 v. 225 amps at 480 v.	12,000 lbs	7'W x 8'4"H x 17'4"L
230 kW	100% load = 18.3 75% load = 13.4 50% load = 9.1	400	781 amps at 208 v. 330 amps at 480 v.	16,550 lbs	8.4'W x 9.5'H x 20.5'L
300 kW	100% load = 23.5 75% load = 16.8 50% load = 11.8	400	1040 amps at 208 v. 451 amps at 480 v.	16,550 lbs	8.4'W x 9.5'H x 20.5'L
400 kW	100% load = 28 75% load = 21 50% load = 14	520	1390 amps at 208 v. 602 amps at 208 v.	20,458 lbs	8.5'W x 10.8'H x 22.2'L

